# eID – Electronic Identification

# **1** Introduction

The Electronic Identity card usage is a feature originally developed for the Belgian market. It has system and license implications.

#### Licence information

Note that EIK is not a standard part of the Vubis Smart application. It requires a specific license and must be installed and activated separately. Please contact your account manager for pricing and installation information.

The Belgium Electronic Identity card is used in Vubis Smart in two ways:

- Vubis Smart client
  - Logon to the Vubis Smart server
  - Borrower identification
- Vubis Smart WebOpac
  - Borrower identification

## **2 Vubis Smart Client**

When a form is eID (=electronic IDentity) enabled, the title bar of that form will show 'eID'.

This means that the eID can be used for input on that form. When a card is inserted the eID assistant software reads the data from the card. The system can be configured to ask for a pin code when reading this card. By asking for a pin code, the system then knows that a valid person is using the card.

### 2.1 Vubis Smart logon (staff)

When the Vubis Smart Login screen is shown, the user can use the eID to logon.

🗣 Vubis Smart - Login screen - elD	$\mathbf{X}$
Enter your login and password to access to the Vubis Smart data server.	ок
Login	Cancel
Password	Help

After inserting the eID card, the user will be asked to enter the pin code:

ntity	
Enter your PIN, in order to au	Ithenticate yourself
PIN:	
QK	<u>C</u> ancel

This is configured in AFO 611 option 1, 'Add/modify logins'.

Only one identity card per Vubis Smart password is permitted.

To allow the eID for a certain password, choose that password in the above mentioned option. After this is selected the following form is presented:

Agin ID : VGG	
- Login ID VGG Language eng Databases 2 Permited to switch to Inst/Loc(s) * Date added 0 Email address Service point eID 71715100070 Inst/Loc(s) for editing items *	
- Login ID VGG Language eng Databases 2 Permited to switch to Inst/Loc(s) * Date added 0 Email address Service point eID 71715100070 Inst/Loc(s) for editing items *	
Name         Mathijs           Language         eng           Databases         2           Password required? 1=Yes         0           Permitted to switch to Inst/Loc(s)         *           Date added         08 Aug 2003           Memory option         0           Email address         -           Service point         -           eID         7/171500070           Inst/Loc(s) for editing items         *	
Name         Mathijs           Language         eng           Databases         2           Password required? 1=Yes         0           Permitted to switch to Inst/Loc(s)         *           Date added         08 Aug 2003           Memory option         0           Email address            Service point         -           elD         7/171500070           Inst/Loc(s) for editing items         *	
Name         Mathijs           Language         eng           Databases         2           Password required? 1=Yes         0           Permitted to switch to Inst/Loc(s)         *           Date added         08 Aug 2003           Memory option         0           Email address            Service point         -           elD         7/171500070           Inst/Loc(s) for editing items         *	
Language         eng           Databases         2           Databases         2           Password required? 1=Yes         0           Permitted to switch to Inst/Loc(s)         *           Date added         08 Aug 2003           Memory option         0           Email address         Service point           alD         7/171500070           Inst/Loc(s) for editing items         *	
Databases     2       Password required? 1=Yes     0       Permitted to switch to Inst/Loc(s)     *       Date added     08 Aug 2003       Memory option     0       Email address     *       Service point     71715100070       Inst/Loc(s) for editing items     *	
Password required? I=Yes         0           Permitted to switch to Inst/Loc(s)         *           Date added         08 Aug 2003           Memory option         0           Email address         *           Service point         *           elD         7/171500070           Inst/Loc(s) for editing items         *	
Date added         08 Aug 2003           Memory option         0           Email address         5           Service point         71715100070           InSt/Loc(s) for editing items         *	
Date added         06 Aug 2003           Memory option         0           Email address	
Memory option         0           Email address         Service point           eID         71715100070           Inst/Loc(s) for editing items         *	
Email address Service point eID 71715100070 Inst/Loc(s) for editing items *	
eID 71715100070 Inst/Loc(s) for editing items *	
eID 71715100070 Inst/Loc(s) for editing items *	
Inst/Loc(s) for editing items * Inst/Loc(s) for deleting items PNB/BD	
i Inst/Loc(s) for deleting items PNB/BD	

Choose option 13 on this screen, 'eID'. The following form appears:

🗝 Modify data for Login ID - eID	
eID Identification	
	ок
	Cancel
	Help

Use the eID reader and card, to add the ID number to this password. After this is done, the user can logon using his/her eID.

### 2.2 Borrower identification (AFO 431)

After choosing AFO 431 ('Borrower administration') the following eID enabled form is displayed:

🔲 Identify a borrower -	eID		×
Borrower name/barcode			
		ОК	
		Cancel	
		<u>H</u> elp	
		New record	
		Previous	
		Advanced	
		<u>_</u>	1

The borrower can enter his/her eID, which is then read. (The library can configure that a pin code is necessary upon reading the card.)

The Vubis Smart system will try to find the borrower using the card number read. If it can't find the number the system will perform a search on the name of the borrower. If the name is found then the system will update the borrower record, either automatic or after confirmation by the staff member. (It can also be configured that no action is taken).

If it is configured that the staff member has to confirm changes to the database, then the following form will appear, whenever a difference is detected between eID card data and the Vubis Smart data:

Vubis Smar	t	
	detected between eID card & Vubis Smart database!	
Overwrite	existing data with data from eID card?	
Card	29/79/1979	
	Liège	
	4000	
	Addresse Caractères Spéciaux : ø?çà??	
Database		
	Werkhoven	
	5433	OK
	Rijksstraatweg 243	Cancel

The following workflow should be used if the system can't find the borrower by name (because of incorrect entry in the Vubis Smart database).

Search for the borrowers record manually, by either using the 'old' library card, or a manual search on the borrowers name. After the record is presented on screen, choose option 1, 'Barcode'. The following form is then presented:

🔲 Add / modify current barcode - elD	
Borrower's barcode	
	ок
	Cancel
	Help
	Automatic
	EX /

Insert the eID card, and the existing barcode is replaced by the eID.

Note

The borrowers record isn't updated here with all other fields, but the server can now find the borrower using the eID.

### 3 WebOpac

When the user opts for logon using eID in the WebOpac, the following form is displayed, when using Internet Explorer.

Note

FireFox is currently not supported because it doesn't allow OCX, to run within the browser.

The user has to have an eID reader, as well as the proper software installed; eID runtime supplied by Fedict Belgium. When this is installed and this form is opened the browser will ask confirmation of downloading and running the OCX.

Inloggen in Vubis Smart m.b.v. elK - Microsoft Internet Explorer			
Eile Edit View Favorites Iools Help	A.		
🔇 🔹 🔊 🔹 🐣 Address 🛃 http://localhost/vsdevwomathijs/eIK.csp?OpacLan	guage=dut&Profile=Default&Req. 🔽 🄁 Go		
<b>Inloggen in Vubis Smart m.b.v</b> Om deze functie te kunnen gebruiken dient u uw Elektronische identiteit:			
Gegevens op u <del>w</del> Identiteitskaart			
Rijksregister nummer			
Naam			
Adres			
Geboortedatum/plaats			
Kaart nummer Geldigheidsduur			
, , , , , , , , , , , , , , , , , , , ,			
Geen kaart in lezer aanwezig.	© http://www.cevi.be		
	le http://www.combo		
Inloggen			
Het verwerken van de gegevens gebeurt conform de wet tot bescherming van de persoonlijke levenssfeer (Wet 8/12/1992)			
	© 19/11/2004 Cevi NV © 10/10/2005 Geac Benelux b <i>x</i> .		
	×		
Cone	Second Intranet		

When the data is read, the OCX will ask the user for a pin code. If the entered pin code is valid, the Vubis Smart system will automatically log the user on the system.

Id	Identity			
	Caution: You are about to make a legally binding electronic signature with your identity card. Please enter your PIN to continue or click the Cancel button. Warning: if you only want to log on to a web site or server, do NOT enter your PIN and click the Cancel button.			
	PIN:			
	OK <u>C</u> ancel			

#### Document control - Change History

Version	Date	Change description	Author
1.0	September 2006	creation (delivered as part of build 17 updates)	